

Steca PA RC100

Remote control

Steca PA RC100 remote control allows to program Steca solar charge controllers. The values can be adjusted with the help of switches. After a restart of the charge controller the new settings can be activated by pressing the program-button on the Steca PA RC100. An LED will transfer the values to the controller.

Product features

- Low weight
- Simple installation
- Maintenance-free
- Low own consumption
- Best reliability



	PA RC100
Characterisation of the operating performance	
Supply voltage	4.5 V (3 x 1.5 V AAA / R03 batteries)
Adjustable parameters	– Type of battery: gel / liquid – Night-light function – End of charge voltages (float / boost / equal) – Deep discharge protection (LVD) – LVD factor – Switch-on threshold
Suitable for the following Steca charge controllers	– Steca Solsum F – Steca PRS – Steca Solarix MPPT 1010/2010
Fitting and construction	
Dimensions (X x Y x Z)	115 x 57 x 20 mm
Weight	90 g

Areas of application:



Technical data at 25 °C / 77 °F