

AC Current

Range	Resolution	Accuracy	Overload Protection
		45~400Hz	
20mA	10µA	±(1.0%+3)	Fuse: 200mA/250V, φ5 x 20mm
200mA	100µA	±(1.8%+3)	
10A	10mA	±(3.0%+5)	Fuse : 10A/250V, φ6 x 25mm

Remarks:

- Maximum input current: 10A (For current over 5A: measuring time shall not exceed 15 second)
- Measured voltage drop: 200mV for all range
- Display: Mean value (RMS vale of sinewave)

AC Current

Range	Resolution	Accuracy	Overload Protection
		40~400Hz	
20mA	10µA	±(1.0%+3)	0.5A. 250V fast type fuse,
200mA	100µA	±(1.8%+3)	5x20mm
20A	10mA	±(3.0%+5)	No Fused

Remarks:

- At 20A Range: For continuous measurement 10seconds and interval not less than 15 minutes
- Measured voltage drop: 200mV for all range
- Display effective value of sine wave (mean value response)

Resistance

Range	Resolution	Accuracy	Overload Protection
200Ω	0.1Ω	±(1.2%+2)	
2kΩ	1Ω		
20kΩ	10Ω	±(1.0%+2)	
200kΩ	100Ω		
2MΩ	1kΩ	±(1.2%+2)	
20MΩ	10kΩ	±(1.5%+2)	
			250V dc or ac (rms)

Remarks:

- Open circuit voltage: ≤ 700mV

Resistance

Range	Resolution	Accuracy	Overload Protection
200Ω	0.1Ω	±(0.8%+3)	
2kΩ	1Ω		
20kΩ	10Ω	±(0.8%+1)	
200kΩ	100Ω		
2MΩ	1kΩ		
200MΩ	100kΩ	±[5.0%(rdg-10)+10]	250V dc or ac (rms)

Remarks:

- Open circuit voltage: 700mV (At 200MΩ range, it is approx. 2.8V)
- At 200MΩ range , test lead is in short circuit , and it is normal to display 10 digits. During measurement, subtract the 10 digits from the reading.

Capacitance

Range	Resolution	Accuracy	Overload Protection
2nF	1pF		
20nF	10pF		
200nF	100pF	±(4.0%+3)	
2µF	1nF		
200µF	100nF	≤ 50µF: ±(5.0%+4) > 50µF: unspecified	mA to V terminal : 200mA/250V, φ5 x 20mm

Remarks:

- The test signal is about 400Hz, 40mVrms

Capacitance

Range	Resolution	Accuracy	Overload Protection
20nF	10pF		
200nF	0.1nF	±(4.0%+3)	
2µF	1nF		
100µF	100nF	≤ 30µF: ±(5.0%+4) > 30µF: unspecified	mA to V terminal : 250Vac

Remarks:

- The test signal is about 400Hz, 40mVrms

<h3>Frequency</h3> <ul style="list-style-type: none"> • Overload Protection: 250V AC • Input sensitivity: $\leq 200\text{mVrms}$ 	<table border="1"> <thead> <tr> <th colspan="4">Frequency</th> </tr> <tr> <th>Model</th><th>Range</th><th>Accuracy</th><th>Maximum Resolution</th></tr> </thead> <tbody> <tr> <td>Frequency</td><td>2kHz</td><td>$\pm(2.0\%+5)$</td><td>1Hz</td></tr> <tr> <td></td><td>20kHz</td><td>$\pm(1.5\%+5)$</td><td>10Hz</td></tr> </tbody> </table>	Frequency				Model	Range	Accuracy	Maximum Resolution	Frequency	2kHz	$\pm(2.0\%+5)$	1Hz		20kHz	$\pm(1.5\%+5)$	10Hz				
Frequency																					
Model	Range	Accuracy	Maximum Resolution																		
Frequency	2kHz	$\pm(2.0\%+5)$	1Hz																		
	20kHz	$\pm(1.5\%+5)$	10Hz																		
<h3>Diode Test</h3> <table border="1"> <thead> <tr> <th>Range</th><th>Instructions</th><th>Testing conditions</th></tr> </thead> <tbody> <tr> <td>►</td><td>Display the forward voltage of diode (approximate value), unit "mV"</td><td>Forward DC current is about 1mA and reverse DC voltage is about 2.8V</td></tr> </tbody> </table> <ul style="list-style-type: none"> • Overload Protection: 250Vdc or ac effective value 	Range	Instructions	Testing conditions	►	Display the forward voltage of diode (approximate value), unit "mV"	Forward DC current is about 1mA and reverse DC voltage is about 2.8V	<h3>Diode Test</h3> <table border="1"> <thead> <tr> <th>Range</th><th>Instructions</th><th>Testing conditions</th></tr> </thead> <tbody> <tr> <td>►</td><td>Display approximate value (500~800 mV) of forward voltage drop for diode</td><td>Open circuit is about 2.8V</td></tr> </tbody> </table> <ul style="list-style-type: none"> • Overload Protection: 250Vdc or ac • Resolution: 1mV 	Range	Instructions	Testing conditions	►	Display approximate value (500~800 mV) of forward voltage drop for diode	Open circuit is about 2.8V								
Range	Instructions	Testing conditions																			
►	Display the forward voltage of diode (approximate value), unit "mV"	Forward DC current is about 1mA and reverse DC voltage is about 2.8V																			
Range	Instructions	Testing conditions																			
►	Display approximate value (500~800 mV) of forward voltage drop for diode	Open circuit is about 2.8V																			
<h3>Continuity Test</h3> <table border="1"> <thead> <tr> <th>Range</th><th>Resolution</th><th>Testing conditions</th></tr> </thead> <tbody> <tr> <td>●))</td><td>If resistance $\leq 10\Omega$, the buzzer sounds; Display approximate resistance value, unit "Ω"</td><td>Open circuit voltage is about 2.8V</td></tr> </tbody> </table> <ul style="list-style-type: none"> • Overload Protection: 250Vdc or ac effective value 	Range	Resolution	Testing conditions	●))	If resistance $\leq 10\Omega$, the buzzer sounds; Display approximate resistance value, unit " Ω "	Open circuit voltage is about 2.8V	<h3>Continuity Test</h3> <table border="1"> <thead> <tr> <th>Range</th><th>Resolution</th><th>Testing conditions</th></tr> </thead> <tbody> <tr> <td>♪</td><td>1Ω</td><td>If resistance $\leq 70\Omega$, the buzzer sounds</td></tr> </tbody> </table> <ul style="list-style-type: none"> • Overload Protection: 250Vdc or ac • 	Range	Resolution	Testing conditions	♪	1 Ω	If resistance $\leq 70\Omega$, the buzzer sounds								
Range	Resolution	Testing conditions																			
●))	If resistance $\leq 10\Omega$, the buzzer sounds; Display approximate resistance value, unit " Ω "	Open circuit voltage is about 2.8V																			
Range	Resolution	Testing conditions																			
♪	1 Ω	If resistance $\leq 70\Omega$, the buzzer sounds																			
<h3>Temperature Measurement</h3> <table border="1"> <thead> <tr> <th>Range</th><th>Resolution</th><th>Accuracy</th></tr> </thead> <tbody> <tr> <td>°C</td><td>1°C</td><td>(-40~0°C): $\pm(3.0\%+9)$ (>0~400°C): $\pm(1.0\%+5)$ (>400~1000°C): $\pm(2.0\%+10)$</td></tr> <tr> <td>°F</td><td>2°F</td><td>(-40~32°F): $\pm(3.0\%+10)$ (>32~752°F): $\pm(1.0\%+8)$ (>752~1832°F): $\pm(2.0\%+18)$</td></tr> </tbody> </table>	Range	Resolution	Accuracy	°C	1°C	(-40~0°C): $\pm(3.0\%+9)$ (>0~400°C): $\pm(1.0\%+5)$ (>400~1000°C): $\pm(2.0\%+10)$	°F	2°F	(-40~32°F): $\pm(3.0\%+10)$ (>32~752°F): $\pm(1.0\%+8)$ (>752~1832°F): $\pm(2.0\%+18)$	<h3>Temperature Measurement</h3> <table border="1"> <thead> <tr> <th>Range</th><th>Resolution</th><th>Accuracy</th><th>Overload Protection</th></tr> </thead> <tbody> <tr> <td>°C</td><td>1°C</td><td>(-40~0°C): $\pm(3.0\%+9)$ (>0~400°C): $\pm(1.0\%+7)$ (>400~1000°C): $\pm(2.0\%+10)$</td><td rowspan="3">250V AC</td></tr> <tr> <td>°F</td><td>2°F</td><td>(-40~32°F): $\pm(3.0\%+10)$ (>32~752°F): $\pm(1.0\%+8)$ (>752~1832°F): $\pm(2.0\%+18)$</td></tr> </tbody> </table>	Range	Resolution	Accuracy	Overload Protection	°C	1°C	(-40~0°C): $\pm(3.0\%+9)$ (>0~400°C): $\pm(1.0\%+7)$ (>400~1000°C): $\pm(2.0\%+10)$	250V AC	°F	2°F	(-40~32°F): $\pm(3.0\%+10)$ (>32~752°F): $\pm(1.0\%+8)$ (>752~1832°F): $\pm(2.0\%+18)$
Range	Resolution	Accuracy																			
°C	1°C	(-40~0°C): $\pm(3.0\%+9)$ (>0~400°C): $\pm(1.0\%+5)$ (>400~1000°C): $\pm(2.0\%+10)$																			
°F	2°F	(-40~32°F): $\pm(3.0\%+10)$ (>32~752°F): $\pm(1.0\%+8)$ (>752~1832°F): $\pm(2.0\%+18)$																			
Range	Resolution	Accuracy	Overload Protection																		
°C	1°C	(-40~0°C): $\pm(3.0\%+9)$ (>0~400°C): $\pm(1.0\%+7)$ (>400~1000°C): $\pm(2.0\%+10)$	250V AC																		
°F	2°F	(-40~32°F): $\pm(3.0\%+10)$ (>32~752°F): $\pm(1.0\%+8)$ (>752~1832°F): $\pm(2.0\%+18)$																			

Other Functions

MODEL	GDM-357
Max. Display	1999
Auto Ranging	
Analog Bar	
True RMS	
Display Backlight	
Fused 10A Range	✓
Auto Power off	✓
Diode	✓
Continuity	✓
Temperature	✓
Duty Cycle(%)	
Transistor (hFE)	
REL	
Data Hold	✓
Peak Hold	
MAX MIN	
RS232C	



Other Functions:

MODEL	GDM-356
Max. Display	1999
Auto Ranging	
Analog Bar	
True RMS	
Display Backlight	✓
Fused 10A Range	
Auto Power off	✓
Diode	✓
Continuity	✓
Temperature	✓
Duty Cycle(%)	
Transistor (hFE)	
REL	
Data Hold	✓
Peak Hold	
MAX MIN	
RS232C	

