

2 SD 2015	Si-N-Darl+Di	NF/S-L, 150/120V, 4A, 25W,40MHz,B>2000	17c	-		
2 SD 2016	Si-N-Darl+Di	NF/S-L, 250/200V, 3A, 25W,90MHz,B>1000	17c	-		
2 SD 2017	Si-N-Darl+Di	S-L, 300/250V, 6A, 35W, B>2000	17c	-		
2 SD 2018	Si-N-Darl+Di	int. Z-Di, 60V, 1A, 5W, 150MHz, B>6500	14b	-		
2 SD 2019	Si-N-Darl+Di	NF-L, 150V, 1,5A, 10W, B>5000	14h	2SD986	14h	
2 SD 2020	Si-N	NF/S-L, 150V, 2A, 40W	17j	2SD1138	17j	
2 SD 2021	Si-N	=2SD2020: Iso, 30W	17c	(2SD1138)	17j	3
2 SD 2022	Si-N-Darl+Di	int.Z-Di(B →C), 60V, 1,5A, 25W, B=3000	17j	BD 901	17j	
2 SD 2023	Si-N	NF/S-L, 80V, 3A, 40W, 8MHz	17j	BD 243 C	17j	
2 SD 2024	Si-N-Darl+Di	NF/S-L, 100V, 8A, 40W, B=10000	17j	-		
2 SD 2025	Si-N-Darl+Di	=2SD2024: Iso, 30W	17c	-		
2 SD 2027	Si-N	NF/S-L, 60V, 3A, 30W, 8MHz	17j	BD 243 C	17j	
2 SD 2029	Si-N	S-L, 160/160V, 12A, 120W, 20MHz	77j	2SC3281	77j	
2 SD 2030	Si-N	=2SD1868: 0,4W	7c	BF 420 A	7c	
2 SD 2031	Si-N	=2SD1869: 0,4W	7c	BF 420 A	7c	
2 SD 2032	Si-N-Darl+Di	NF/S-L, 80V, 4A, 20W, B=3000	78c	(BD 679)	14h	4
2 SD 2033	Si-N	NF/S-L, 120V, 1,5A, 1,8W, 80MHz	78c	(2SC3117)	14h	4
2 SD 2033 A	Si-N	=2SD2033: 160V	78c	(2SC3117)	14h	4
2 SD 2034	Si-N	NF/S-L, 80V, 3A, 25W	78c	(BD 189)	14h	4
2 SD 2035	Si-N	NF/S-L, 80V, 4A, 1,8W, 8MHz	78c	(BD 189)	14h	4
2 SD 2036	Si-N	NF/S-L, 100V, 7A, 1,8W, 5MHz	78c	-		
2 SD 2037	Si-N	NF/S-L, 60V, 3A, 1,8W, 90MHz	78c	(2SD1348)	14h	4
2 SD 2038	Si-N	NF/S-L, 80V, 5A, 1,8W, 8MHz	78c	-		
2 SD 2039	Si-N-Darl+Di	NF/S-L, 100V, 2A, 1,8W, B=4000	78c	(2SD986)	14h	4
2 SD 2040	Si-N	NF/S-L, 100V, 5A, 1,8W, 8MHz	78c	-		
2 SD 2041	Si-N-Darl+Di	int. Z-Di(B →C), 60V, 2A, B=4000	78c	-		
2 SD 2042	Si-N-Darl+Di	int. Z-Di(B →C), 60V, 5A, B=10000	78c	-		
2 SD 2043	Si-N-Darl+Di	NF/S-L, 120V, 6A, B=10000	78c	-		
2 SD 2044	Si-N	NF/S-L, hi-beta, 80V, 3A, B=400...2000	78c	-		
2 SD 2045	Si-N-Darl+Di	NF/S-L, 120V, 6A, 50W, 50MHz, B>2000	18c	-		
2 SD 2046	Si-N-Darl+Di	int. Z-Di, 50V, 1,5A, 1W, B=2k...10k	7c(9mm)	-		
2 SD 2047(R)	Si-N	S-L, TV-HA, 1500V, 5A, 80W	18c	2SD1577	16c	
2 SD 2048	Si-N-Darl+Di	NF/S-L, 110V, 3A, 30W, 20MHz, B=4000	30j	-		
2 SD 2049	Si-N-Darl+Di	NF/S-L, 110V, 5A, 35W, 20MHz, B=4000	30j	-		
2 SD 2050	Si-N-Darl+Di	NF/S-L, 110V, 8A, 40W, 20MHz, B=4000	30j	-		
2 SD 2051	Si-N-Darl+Di	int.Z-Di, 60V, 1,6A, 12W, >200MHz,B>4k	17c	-		
2 SD 2052	Si-N	NF/S-L, 150/150V, 9A, 100W, 20MHz	16c	(2SC2837)	18j	3
2 SD 2053	Si-N	=2SD2052:	18j	2SC2837	18j	
2 SD 2055	Si-N	NF/S-L, 80V, 10A, 40W	17j	BD 809	17j	
2 SD 2056	Si-N	=2SD2055: Iso, 30W	17c	(BD 809)	17j	
2 SD 2057	Si-N+Di	S-L, TV-HA, 1500/700V, 5A, 100W	16c	BU 2508 DF	16c	
2 SD 2058	Si-N	NF/S-L, 60V, 3A, 25W, 3MHz, <0,8/2,3µs	17c	2SC3299	17c	
2 SD 2059	Si-N	NF/S-L, 100V, 5A, 30W, 12MHz	17c	2SD1411	17c	
2 SD 2060	Si-N	NF/S-L, 80V, 4A, 25W, 8MHz	17c	2SD1411	17c	
2 SD 2061	Si-N	=2SD2023: Iso, 30W	17c	2SD1411	17c	
2 SD 2062	Si-N	NF/S-L, 100/80V, 7A, 80W, 8MHz	16c(j)	(BD 245 C)	18j	3
2 SD 2063	Si-N	NF, hi-beta, 15V, 1A, 0,9W, B=700	7c(9mm)	2SC3225	7c(9mm)	
2 SD 2064	Si-N	NF/S-L, 120/120V, 6A, 70W, 20MHz	16c	2SC2837	18j	
2 SD 2065	Si-N	NF/S-L, 140/140V, 7A, 80W, 20MHz	16c	(2SC2837)	18j	3
2 SD 2066	Si-N	NF/S-L, 160/160V, 12A, 120W, 20MHz	18j	2SD1047	18j	
2 SD 2067	Si-N-Darl+Di	Uni, 120/100V, 2A, 1W, B>4k	9c	-		
2 SD 2068	Si-N-Darl+Di	Uni, int. Z-Di, 60V, 1A, 1W, B>4k	7c(9mm)	2SD1153	7c(9mm)	
2 SD 2069	Si-N	lo-sat, 60V, 2A, 1W, 210MHz	7c(9mm)	2SD1207	9c(9mm)	
2 SD 2070	Si-N	Uni, 50V, 0,1A, 1W	9c	BC 546	7a	
2 SD 2071	Si-N	Uni, 50V, 0,5A, 1W, 200MHz	9c	BC 337	7a	
2 SD 2072	Si-N	=2SD661: 1W, Pins = 14mm	9c	→2SD661		