

2 SC 3396		Si-N+R	=2SC3400: SMD	(2SA1342	35a	SOT-23			KSR 1103
2 SC 3397		Si-N+R	=2SC3401: SMD	(2SA1343	35a	SOT-23			KSR 1108
2 SC 3398		Si-N+R	=2SC3402: SMD	(2SA1344	35a	SOT-23			KSR 1102
2 SC 3399	Say	Si-N+R	S, Rb=Rbe=47kΩ, 50/50V, 0,1/0,2A, 250MHz		41c		(BC 546) ¹⁸	7a	KSR 1004, 2SC3653
2 SC 3400	Say	Si-N+R	S, Rb=Rbe=22kΩ, 50/50V, 0,1/0,2A, 250MHz		41c		(BC 546) ¹⁸	7a	KSR 1003, 2SC3654
2 SC 3401	Say	Si-N+R	S, Rb=46kΩ, Rbe=23kΩ, 50/50V, 0,1/0,2A, 250MHz		41c		(BC 546) ¹⁸	7a	KSR 1008, 2SC3655
2 SC 3402	Say	Si-N+R	S, Rb=Rbe=10kΩ, 50/50V, 0,1/0,2A, 250MHz		41c		(BC 546) ¹⁸	7a	KSR 1002, 2SC3656
2 SC 3403	Mat	Si-N	S P, 500/400V, 2/4A, 25W, >8MHz, <1/4μs		30j	(TO-220MF)	(BUX 85) ⁴	17j	2SC4219, 2SC4597, 2SC4754
2 SC 3404	Mit	Si-N	VHF Drv,Out, 20/9V, 1A, PQ=1,7W(175MHz/7,2V)						
2 SC 3405	Tos	Si-N	S P, 900/800V, 0,8/1,5A, 20W, <1/5μs		30j	TO-251/252	(BUX 85) ⁴	17j	2SC3489, (BUV 95, BUX 85, 2SC3149,++) ⁴
2 SC 3406	Mat	Si-N	UHF P, 36/16V, 3A, PQ=8W(915MHz/12,5V)						
2 SC 3407		Si-N	UHF P, 36/16V, 2A, PQ=3,5W(915MHz/12,5V)						
2 SC 3408	Mat	Si-N	LF, Vid, 300/300V, 0,1A, 10W, 80MHz		30j	TO-251/252	(BF 459) ⁴	14h	2SC2870, 2SC2924, 2SC3805, 2SC4019, ++
2 SC 3409	Sak	Si-N	S P, 900/800V, 2A, 80W, <1/4,8μs		18j	TO-3P	BUW 11 A	18j	BUW 11A, 2SC3152, 2SC3376, 2SC3550, ++
2 SC 3410	Nec	Si-N	UHF P, 35/18V, 2A, PQ=7,2W(500MHz/9,6V)		55s				
2 SC 3411	Hit	Si-N	S P, 800/400V, 10A, 50W, <1/4,5μs		23a	TO-3	S 2530 A	23a	BUS 12(A), BUW 26, BUW 35...36, 2SC3049++
2 SC 3412	Hit, Tho	Si-N	TV-HA, 1200/500V, 8A, 50W, <1/4,5μs, sat<5V(1A)		23a	TO-3	(BU 903) ⁷	18j	BU 137A, MJ 8504...8505, 2SC3215, ++
2 SC 3413	Hit	Si-N	Uni, 40/30V, 0,1A, 0,3W, 200MHz, F<5dB(1kHz)		41c	(SPAK)	BC 546	7a	BC 167, BC 182, BC 237, BC 547, 2SC2390+
2 SC 3414		Si-N	=2SC3413: 0,4W		9c		BC 546	7a	BC 167, BC 182, BC 237, BC 547, ++
2 SC 3415	Rhm	Si-N	=2SC3269: 0,5W		7c	TO-92	BF 420A	7c	BF 299, BF 393, BF 420A, 2SC3468, ++
2 SC 3416	Say	Si-N	Vid, hi-def, 200/200V, 0,1/0,2A, 5W, 70MHz	(2SA1352	14h	TO-126	2SC3503	14h	2SC3502...03, (BF 415, BF 417,++)
2 SC 3417		Si-N	=2SC3416: 300/300V	(2SA1353	14h	TO-126	2SC3503	14h	2SC3503, (BF 417)
2 SC 3418		Si-N	=2SC3416: 400/400V, 100MHz	(2SA1354	14h	TO-126			(BF 850)
2 SC 3419	Tos	Si-N	40/40V, 0,8A, 5W, 100MHz, sat<0,8V(0,5A)	(2SA1356	14b	TO-126 Iso	(BD 139) ³	14h	2SD1684, (BD 135, BD 226, BD 375) ³
2 SC 3420	Tos	Si-N	50/20V, 5/8A, 10W, 100MHz, sat<1V(4A)	(2SA1357	14b	TO-126 Iso	2SC3420	14b	2SD1685, (2SC2270, 2SD826) ³
2 SC 3421	Tos	Si-N	LF,HF/S P, 120/120V, 1A, 10W, 120MHz	(2SA1358	14b	TO-126 Iso	2SC3117	14h	2SC3621, 2SD1381, 2SD1684 ³
2 SC 3422	Tos	Si-N	LF,HF/S P, 40/40V, 3A, 10W, 100MHz	(2SA1359	14b	TO-126 Iso	2SC3422	14h	2SD1683, 2SD1685, (BD 785, MJ E 240...242) ³
2 SC 3423	Tos	Si-N	LF P, 150/150V, 0,05A, 5W, 200MHz	(2SA1360	14b	TO-126 Iso	(BF 471) ³	14h	2SC3787...88, 2SC3956, (BF 415, BF 469,++) ³
2 SC 3424	Tos	Si-N	S/Vid P, 250/250V, 0,05A, 80MHz	(2SA1361	14b	TO-126 Iso	(BF 471) ³	14h	2SC3789...90, (BF 415, BF 417, BF 469,++) ³
2 SC 3425	Tos	Si-N	S P, 500/400V, 0,8/1,5A, 10W, <1/4μs		14h	TO-126			BD 410, 2SC3051
2 SC 3426	Tos	Si-N	SMD, 15/15V, 0,8A, 120MHz, sat<0,2V(0,4A)	(2SA1362	35a	SOT-23			BCW 65...66, 2SC3265
2 SC 3427	Shi	Si-N	LF,S P, 50/30V, 7A, 50W, <200/2300ns, hFE>100		17j	TO-220	BD 809	17j	BD 543A, BD 797, BD 805
2 SC 3428	Shi	Si-N	LF,S P, 60/40V, 10A, 50W, <200/2300ns, hFE=85		17j	TO-220	BD 809	17j	BD 707, BD 743A, BD 807
2 SC 3429	Tos	Si-N	SMD, UHF, 17/12V, 0,07A, 5GHz, F=1,7dB(1GHz)		35a	SOT-23			2SC3161
2 SC 3430	Nec	Si-N	S P, 500/400V, 2A, 20W, <0,5/1,8μs		15j	(MP-40)	BUX 85	17j	BUX 84...85, 2SC2333, 2SC2534, 2SC2738,++
2 SC 3431	Nec	Si-N	S P, 500/400V, 5/10A, 40W, <0,5/1,8μs		15j	(MP-40)	BUT 11 A	17j	BUT 11(A), BUW 46(A), 2SC2827, 2SC3497,++
2 SC 3432	Nec	Si-N	S P, 500/400V, 7/15A, 60W, <0,5/1,8μs		15j	(MP-40)	BUT 56 A	17j	BUT 56(A), 2SC3039, 2SC3170, 2SC4106, ++
2 SC 3433	Nec	Si-N	S P, 500/400V, 10A, 60W, <0,5/1,8μs		15j	(MP-40)	BUT 12 A	17j	BUW 56(A), BUW 66(A), 2SC3562, ++
2 SC 3434	Nec	Si-N	S P, 500/400V, 10/20A, 100W, 30MHz, <0,5/1,8μs		16j	(MP-80)	BUW 13 A	18j	BUW 47(A), BUW 12(A), 2SC2828, 2SC3042,++
2 SC 3435	Nec	Si-N	S P, 500/400V, 15/30A, 120W, 30MHz, <0,5/1,8μs		16j	(MP-80)	BUW 13 A	18j	BUW 48(A), BUW 13(A), 2SC4139...40, ++
2 SC 3436	Nec	Si-N	S P, 500/500V, 20A, 200W, <1/1,7μs		20j				
2 SC 3437	Tos	Si-N	SMD, HF,S, 40/15V, 0,2A, 400MHz, 70/45ns		35a	SOT-23			BSR 17, 2SC3392, 2SC3739, 2SC4453
2 SC 3438	Mit	Si-N	SMD, Uni, 100/100V, 0,5/0,8A, 130MHz	(2SA1368	39b	SOT-89			2SC2881, 2SD968(A), 2SD1006...1007
2 SC 3439	Mit	Si-N	SMD, 30/25V, 1,5/3A, 130MHz, lo-sat<0,5V(1A)		39b	SOT-89			(2SC2982, 2SD1621) ¹³
2 SC 3440	Mit	Si-N	SMD, Uni, 25/20V, 0,7/1A, 180MHz	(2SA1369	35a	SOT-23			BCW 65...66
2 SC 3441	Mit	Si-N	SMD, Uni, 55/50V, 0,4/0,6A, 150MHz	(2SA1366	35a	SOT-23			BCW 65...66, BCX 41
2 SC 3442	Mit	Si-N	Uni, 50/50V, 0,1A, 0,3W, 100MHz		41c		BC 546	7a	BC 167, BC 182, BC 237, BC 547, ++
2 SC 3443	Mit	Si-N	SMD, 20/16V, 2/3A, 80MHz, sat<0,3V(1A)	(2SA1362	39b	SOT-89			2SC2982, 2SC3439, 2SD1621
2 SC 3444	Mit	Si-N	SMD, 60/60V, 1/2A, 80MHz, sat<0,3V(0,5A)	(2SA1364	39b	SOT-89			2SC4409, 2SD1622...1623
2 SC 3445	Tos	Si-N	SMD, UHF, 15/7,5V, 80mA, 7GHz, F=2,3dB(1GHz)		35a	SOT-23	2SC3356	35a	2SC3356
2 SC 3446	Say	Si-N	S P, 800/500V, 3/6A, 50W, <0,5/3,3μs		17j	TO-220	BUT 11 A	17j	BUT 11(A), BUW 46(A), 2SC3047, 2SC3087,++
2 SC 3447	Say	Si-N	S P, 800/500V, 5/10A, 50W, 18MHz, <0,5/3,3μs		17j	TO-220	BUT 11 A	17j	BUT 11(A), BUW 46(A), 2SC3087, 2SC3353,++
2 SC 3448	Say	Si-N	S P, 800/500V, 4/8A, 60W, 18MHz, <0,5/3,3μs		18j	TO-3P	BUW 11 A	18j	BUW 11(A), BUW 131(A), 2SC3088, 2SC3796,++
2 SC 3449	Say	Si-N	S P, 800/500V, 7/14A, 80W, 18MHz, <0,5/3,3μs		18j	TO-3P	BU 426 A	18j	BU 426(A), BU 926, 2SC3089, 2SC3536, ++
2 SC 3450	Say	Si-N	S P, 800/500V, 10/20A, 90W, 18MHz, <0,5/3,3μs		18j	TO-3P	BUV 70	18j	BUV 47(A), BUW 12(A), 2SC3090, 2SC3637,++
2 SC 3451	Say	Si-N	S P, 800/500V, 15/25A, 100W, 18MHz, <0,5/3,3μs		18j	TO-3P	BUW 13 A	18j	BUV 48(A...C), BUW 13(A), 2SC3552
2 SC 3452	Say	Si-N	S P, 800/500V, 7A, 70W, <0,5/3,3μs		23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), BUX 47(A), ++
2 SC 3453	Say	Si-N	S P, 800/500V, 10A, 100W, <0,5/3,3μs		23a	TO-3	S 2530 A	23a	BUS 12(A), BUW 26, BUW 35...35, 2SC3049,++
2 SC 3454	Say	Si-N	S P, 800/500V, 15A, 120W, <0,5/3,3μs		23a	TO-3			BUS 13(A), BUW 45...46, BUX 48(A...C), ++
2 SC 3455	Say	Si-N	S P, 800/500V, 25/40A, 160W, 18MHz, <0,5/3,3μs		23a	TO-3			BUS 14(A), BUS 98(A)
2 SC 3456	Say	Si-N	S P, 1100/800V, 1,5/5A, 40W, 15MHz, <0,5/3,3μs		17j	TO-220	2SC3457	17j	MJE 8500...8501, 2SC3178, 2SC4230
2 SC 3457	Say	Si-N	S P, 1100/800V, 3/10A, 50W, 15MHz, <0,5/3,3μs		17j	TO-220	2SC3457	17j	MJE 8502...8503, 2SC3050
2 SC 3458	Say	Si-N	S P, 1100/800V, 3/10A, 80W, 15MHz, <0,5/3,3μs		18j	TO-3P	2SC3459	18j	2SC3387, 2SC3642
2 SC 3459	Say	Si-N	S P, 1100/800V, 4,5/15A, 90W, 15MHz, <0,5/3,3μs		18j	TO-3P	2SC3459	18j	2SC3387, 2SC3642
2 SC 3460	Say	Si-N	S P, 1100/800V, 6/20A, 100W, 15MHz, <0,5/3,3μs		18j	TO-3P	2SC3461	18j	BU 902...903, 2SC3643
2 SC 3461	Say	Si-N	S P, 1100/800V, 8/25A, 140W, 15MHz, <0,5/3,3μs		18j	TO-3P	2SC3461	18j	BU 902, 2SC3643
2 SC 3462	Say	Si-N	S P, 1100/800V, 4,5A, 100W, 15MHz, <0,5/3,3μs		23a	TO-3	2SC3459	18j	BU 546, MJ 8502...8503, 2SC3343...3344, ++
2 SC 3463	Say	Si-N	S P, 1100/800V, 6A, 120W, <0,5/3,3μs		23a	TO-3	2SC3461	18j	BU 546, MJ 8502...8503, 3SC3343...3344, ++
2 SC 3464	Say	Si-N	S P, 1100/800V, 8A, 130W, <0,5/3,3μs		23a	TO-3	2SC3461	18j	BU 536, MJ 8504...8505, 2SC3412, ++
2 SC 3465	Say	Si-N	S P, 1100/800V, 12/30A, 160W, 15MHz, <0,5/3,3μs		23a	TO-3			BUX 48B,C
2 SC 3466	Say	Si-N	S P, 1200/650V, 8/20A, 120W, 5MHz, <1/4,7μs		18j	TO-3P	2SC3466	18j	MJ 8504...05, 2SC3061, 2SC3215, 2SC4285
2 SC 3467	Say	Si-N	Vid,hi-def, 200/200V, 0,1/0,2A, 1W, 150MHz	(2SA1370	7c(9mm)	TO-92L	2SC3468	7c(9mm)	(BF 420 A)
2 SC 3468		Si-N	=2SC3467: 300/300V	(2SA1371	7c(9mm)	TO-92L	2SC3468	7c(9mm)	(BF 420A)
2 SC 3469		Si-N	=2SC3467: 400/400V	(2SA1372	7c(9mm)	TO-92L	(BF 487)	7c	(2SC4166, 2SC2267, 2SD1385)
2 SC 3470	Hit	Si-N	Uni, 55/50V, 0,1A, 0,3W, 230MHz		41c	(SPAK)	BC 546, BF 255	7a, 7d	BC 237, BC 547, BF 240...41, BF 254...55,++
2 SC 3471	Hit	Si-N	Uni, 60/50V, 0,2A, 0,4W, 250MHz		7b	TO-92	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 SC 3472	Fjd	Si-N-Darl	S P, 900/650V, 3A, 50W, hFE=20, <1/5,5μs		18j	TO-3P			BUT 50P, 2SC3030, 2SC3032
2 SC 3473	Hit	Si-N	P, 50/50V, 4A, 40W, 50MHz, <0,5/2,5μs		17j	TO-220	(BD 243 C) ⁹	17j	2SC2562, 2SC3253, (BD 243A, BD 535,++) ⁹
2 SC 3474	Tos	Si-N	80/80V, 2A, 20W, 85MHz, hi-hFE=500, sat<0,5V(0,3A)		30j	TO-251/252			
2 SC 3475	Tos	Si-N	100/60V, 4/8A, 20W, 20MHz, <0,5/3μs, sat<0,6V(2A)		17c	SOT-186			2SC3540, 2SD1411
2 SC 3476	Mit	Si-N	UHF P, 35/17V, 1,5A, PQ=3,5W(520MHz/12,5V)						
2 SC 3477	Mat	Si-N	UHF, 15/12V, 0,03A, 0,35W, 4,5GHz		25q				BFQ 71...72, 2SC1119, 2SC1336
2 SC 3478(A)	Nec	Si-N	S,Vid, 200/180(A=200)V, 0,1/0,2A, 0,75W, 160MHz		7c	TO-92	BF 420 A	7c	BF 298...299, BF 422, 2SC3467...3468, ++
2 SC 3479	Say	Si-N+Di	TV-HA, hi-def, 1500/800V, 2,5/10A, 80W, sat<8V(2A)	(2SA1376	18j	TO-3P	(BU 508 D)	18j	(BU 705D, 2SD1290...91, 2SD1728, 2SD1876)
2 SC 3480		Si-N+Di	=2SC3479: 3,5/10A, sat<8V(2,5A)		18j	TO-3P	(BU 508 D)	18j	(BU 706D, 2SD1729, 2SD1877)
2 SC 3481	Say	Si-N+Di	TV-HA, hi-def, 1500/800V, 5/16A, 120W, sat<5V(4A)		18j	TO-3P	(BU 508 D)	18j	2SC3681, (BU 508D, 2SD1730, 2SD1878)
2 SC 3482		Si-N+Di	=2SC3481: 6/16A, sat<5V(5A)		18j	TO-3P	(BU 508 D)	18j	2SC3681, (BU 508D, 2SD1731, 2SD1879)
2 SC 3483		Si-N	=2SC3479: ohne/without Damper-Di		18j	TO-3P	(BU 508 A)	18j	(BU 508(A), BU 705, 2SD1493...1494,++)
2 SC 3484		Si-N	=2SC3480: ohne/without Damper-Di		18j	TO-3P	(BU 508 A)	18j	(BU 508(A), BU 706, 2SC3484, 2SD1495)
2 SC 3485		Si-N	=2SC3481: ohne/without Damper-Di		18j	TO-3P	BU 2508 A	18j	2SC3685, (BU 508(A), 2SD1496...97)
2 SC 3486		Si-N	=2SC3482: ohne/without Damper-Di		18j	TO-3P	BU 2508 A	18j	2SC3685...86, (BU 508(A), 2SD1496...1497)