

2 SC 3386	Si-N	NF/S-L, 80/50V, 3A, 10W, <1/3µs	30j	2SC3303	30j	
2 SC 3387	Si-N	S-L, 1200/500V, 5A, 50W, <1/7µs	18j	BU 903	18j	
2 SC 3388	Si-N	S-L, 1200/500V, 5A, 50W, <1/6µs	23a	BU 903	18j	
2 SC 3389	Si-N	Uni, 20V, 2A, 0,7W, 80MHz	7c	2SD1207	7c(9mm)	
2 SC 3390	Si-N	Uni, ra, 55V, 0,1A, 0,3W, 200MHz	41c	BF 959	7d	
				BC 550	7a	
				BF 959	7d	
2 SC 3391	Si-N	VHF, 30V, 0,02A, 0,2W, 940MHz	41c			
2 SC 3392	Si-N	=2SC3393: SMD	35a	-		
2 SC 3393	Si-N	S, 60V, 0,5A, 0,3W, 70/470ns	40c	-		
2 SC 3394	Si-N	Uni, 55V, 0,1A, 0,5W, 230MHz	9c	BC 546	7a	
2 SC 3395	Si-N+R	=2SC3399: SMD	35a	-		
2 SC 3396	Si-N+R	=2SC3400: SMD	35a	-		
2 SC 3397	Si-N+R	=2SC3401: SMD	35a	-		
2 SC 3398	Si-N+R	=2SC3402: SMD	35a	-		
2 SC 3399	Si-N+R	S, Rb=Rbe=47kΩ, 50V, 0,1A, 250MHz	40c	(BC 546)	7a	18
2 SC 3400	Si-N+R	S, Rb=Rbe=22kΩ, 50V, 0,1A, 250MHz	40c	(BC 546)	7a	18
2 SC 3401	Si-N+R	S, Rb=46kΩ, Rbe=23kΩ, 50V, 0,1A, 250MHz	40c	(BC 546)	7a	18
2 SC 3402	Si-N+R	S, Rb=Rbe=10kΩ, 50V, 0,1A, 250MHz	40c	(BC 546)	7a	18
2 SC 3403	Si-N	S-L, 500/400V, 2A, 25W, <1/4µs	30j	(BUX 85)	17j	4
2 SC 3405	Si-N	S-L, 900/800V, 0,8A, 20W, <1/5µs	30j	(BUX 85)	17j	4
2 SC 3408	Si-N	NF/Vid, 300/300V, 0,1A, 10W, 80MHz	30j	(BF 459)	14h	4
2 SC 3409	Si-N	S-L, 900/800V, 2A, 80W, <1/4,8µs	18j	BUW 11 A	18j	
2 SC 3411	Si-N	S-L, 800/400V, 10A, 50W, <1/4,5µs	23a	S 2530 A	23a	
2 SC 3412	Si-N	S-L, TV-HA, 1200/500V, 8A, 50W, <1/4,5µs	23a	BUV 70	18j	
2 SC 3413	Si-N	Uni, 40V, 0,1A, 0,3W, 200MHz	41c	BC 546	7a	
2 SC 3414	Si-N	=2SC3413: 0,4W	9c	BC 546	7a	
2 SC 3415(S)	Si-N	=2SC3269: 0,5W, S: 0,3W	7c, 41c	BF 420A	7c	
2 SC 3416	Si-N	Vid, hi-def, 200/200V, 0,1A, 5W, 70MHz	14h	2SC3503	14h	
2 SC 3417	Si-N	=2SC3416: 300/300V	14h	2SC3503	14h	
2 SC 3418	Si-N	=2SC3416: 400V, 100MHz	14h	-		
2 SC 3419	Si-N	lo-sat, 40V, 0,8A, 5W, 100MHz	14b	2SD1682	14b	
2 SC 3420	Si-N	lo-sat, 50V, 5A, 10W, 100MHz	14b	2SC3420	14b	
2 SC 3421	Si-N	NF/HF/S-L, 120/120V, 1A, 10W, 120MHz	14b	2SC3117	14b	
2 SC 3422	Si-N	NF/HF/S-L, 40V, 3A, 10W, 100MHz	14b	2SC3422	14b	
2 SC 3423	Si-N	NF-L, 150/150V, 0,05A, 5W, 200MHz	14b	(BF 471)	14h	3
2 SC 3424	Si-N	S/Vid-L, 250/250V, 0,05A, 80MHz	14b	(BF 471)	14h	3
2 SC 3425	Si-N	S-L, 500/400V, 0,8A, 10W, -/<4µs	14b	-		
2 SC 3427	Si-N	NF/S-L, 50V, 7A, 50W, <200/2300ns	17j	BD 809	17j	
2 SC 3428	Si-N	NF/S-L, 60V, 10A, 50W, <200/2300ns	17j	BD 809	17j	
2 SC 3430	Si-N	S-L, 500/400V, 2A, 20W, <0,5/1,8µs	15j	BUX 85	17j	
2 SC 3431	Si-N	S-L, 500/400V, 5A, 40W, <0,5/1,8µs	15j	BUT 11 A	17j	
2 SC 3432	Si-N	S-L, 500/400V, 7A, 60W, <0,5/1,8µs	15j	BUT 56 A	17j	
2 SC 3433	Si-N	S-L, 500/400V, 10A, 60W, <0,5/1,8µs	15j	BUT 12 A	17j	
2 SC 3434	Si-N	S-L, 500/400V, 10A, 100W, <0,5/1,8µs	16j	BUW 13 A	18j	
2 SC 3435	Si-N	S-L, 500/400V, 15A, 120W, <0,5/1,8µs	16j	BUW 13 A	18j	
2 SC 3436	Si-N	S-L, 500/500V, 20A, 200W, <1/1,7µs	20j	-		
2 SC 3442	Si-N	Uni, 50V, 0,1A, 0,3W, 100MHz	41c	BC 546	7a	
2 SC 3445	Si-N	SMD, UHF, 15V, 0,08A, 7GHz	35a	2SC3356	35a	
2 SC 3446	Si-N	S-L, 800/500V, 3A, 50W, <0,5/3,3µs	17j	2SC3457	17j	
2 SC 3447	Si-N	S-L, 800/500V, 5A, 50W, <0,5/3,3µs	17j	BUT 11 A	17j	
2 SC 3448	Si-N	S-L, 800/500V, 4A, 60W, <0,5/3,3µs	18j	BUW 11 A	18j	
2 SC 3449	Si-N	S-L, 800/500V, 7A, 80W, <0,5/3,3µs	18j	2SC2834A	18j	
2 SC 3450	Si-N	S-L, 800/500V, 10A, 90W, <0,5/3,3µs	18j	BUW 12 A	18j	
2 SC 3451	Si-N	S-L, 800/500V, 15A, 100W, <0,5/3,3µs	18j	BUW 13 A	18j	
2 SC 3452	Si-N	S-L, 800/500V, 7A, 70W, <0,5/3,3µs	23a	2SC2834A	18j	
2 SC 3453	Si-N	S-L, 800/500V, 10A, 100W, <0,5/3,3µs	23a	S 2530 A	23a	