

2 SK 1190	Sak	MOS-N-FET-e	VFET, 60/20V, 22A, 35W, on<0,05Ω	17c	TO-220 Iso	BUK 445-60, 2SK1095, 2SK1420, 2SK1951,++
2 SK 1191	Sak	MOS-N-FET-e	VFET, 60/20V, 30A, 40W, on<0,08Ω	17c	TO-220 Iso	2SK1257, 2SK1421, 2SK1653, 2SK1952
2 SK 1192	Sak	MOS-N-FET-e	VFET, 60/20V, 40A, 90W, on<28mΩ	18c	TO-3P Iso	2SK1298, 2SK1424, 2SK1666, 2SK2203
2 SK 1193	Sak	MOS-N-FET-e	VFET, 60/20V, 45A, 95W, on<20mΩ	18c	TO-3P Iso	2SK1298, 2SK1424, 2SK1666, 2SK2203
2 SK 1194	Shi	MOS-N-FET-e	VFET, 230/20V, 0,5A, 6W, on<8Ω(0,5), 60/100ns	30c	TO-252	2SK1838, 2SK2199
2 SK 1195	Shi	MOS-N-FET-e	VFET, 230/20V, 1,5A, 10W, <2Ω(1A), 75/110ns	30c	TO-252	2SK375, 2SK535, 2SK945, 2SK1838
2 SK 1196	Mat	GaAs-N-FET	UHF, 6V, 70/200mA, Idss=20...70mA, Up=1-3V F<1,8dB(12GHz)	51(SGSD)	SOT-173	-
2 SK 1197	Hit	MOS-N-FET-e*	VFET, HF Out, 100/9V, 0,5/1A, 20W, on<50Ω	14f	TO-126	-
2 SK 1198	Nec	MOS-N-FET-e	VFET, 700/20V, ±2A, 35W, on<3,2Ω(1A), 20/80ns	17c	-SOT-186	BUK 446-800, 2SK1459, 2SK1611, 2SK1834++
2 SK 1199	Hit	MOS-N-FET-e*	VFET, 900/20V, 2/6A, 50W, on<7Ω(1A), 70/125ns	17p	TO-220	BUZ 50, 2SK1324, 2SK1338
2 SK 1200	Hit	MOS-N-FET-e*	VFET, 900/20V, 3/7A, 80W, on<7Ω(1,5A), 80/120ns	18p	TO-3P	2SK726, 2SK794, 2SK1339, 2SK1341
2 SK 1201	Hit	MOS-N-FET-e*	VFET, 900/20V, 4/107A, 80W, on<5,5Ω(2A), 95/160	18p	TO-3P	BUZ 357...358, 2SK727, 2SK1341, 2SK1760++
2 SK 1202	Hit	MOS-N-FET-e*	VFET, 900/20V, 5/12A, 100W, on<4Ω(3A), 125/220ns	18p	TO-3P	BUZ 357...358, 2SK727, 2SK1341, 2SK1760++
2 SK 1203	Hit	MOS-N-FET-e*	VFET, 900/20V, 6/15A, 100W, on<3Ω(3A), 155/250ns	18p	TO-3P	2SK1342, 2SK1358, 2SK1502, 2SK1614, ++
2 SK 1204	Hit	MOS-N-FET-e*	VFET, 900/20V, 8/20A, 100W, on<1,6Ω(4A), 270/410ns	18p	TO-3P	2SK1342, 2SK1358, 2SK1502, 2SK1614, ++
2 SK 1205	Hit	MOS-N-FET-e*	VFET, 1000/20V, 5/15A, 100W, on<2Ω(3A), 260/430ns	18p	TO-3P	BUZ 357...358, 2SK685, 2SK1359, 2SK1773
2 SK 1206	Hit	MOS-N-FET-e*	=2SK557: Iso, 60W	=18c	(TO-3PFM)	2SK1331, 2SK1523...24
2 SK 1211	Fjd	MOS-N-FET-e	VFET, 800/20V, 2,5A, 40W, <7Ω(1A), 60/110ns	17p	TO-220	BUZ 80, 2SK1199, 2SK1323...24, 2SK1338
2 SK 1212	Fjd	MOS-N-FET-e	VFET, 900/20V, 5A, 80W, <2,5Ω(2,5A), 110/420ns	17p	TO-220	2SK1119, 2SK1501, 2SK1639, 2SK1643
2 SK 1213	Tos	MOS-N-FET-e	VFET, 600/20V, 6/24A, 125W, on<1,25Ω(3A), 40/85ns	18p	TO-3P	BUZ 332A, 2SK684, 2SK1032, 2SK1925
2 SK 1214	Mat	MOS-N-FET-e	VFET, LogL, 80/20V, 20/40A, 45W, <0,135Ω(6A)	17c	SOT-186	2SK1307, 2SK1348...49, 2SK1432, 2SK1906++
2 SK 1215	Hit	MOS-N-FET-d	=2SK359: SMD	35c(2mm)	SOT-323	-
2 SK 1216	Mat	N-FET	SMD, Video-Camera, 10V, 50mA, Idss=9,2...14mA, Up<3V	35f	SOT-23	-
2 SK 1217	Fjd	MOS-N-FET-e	VFET, 900/30V, 8A, 100W, on<2Ω(4A), 280/460ns	17c(p)	TO-220	-
2 SK 1221	Fjd	MOS-N-FET-e	VFET, 250/30V, 10A, 80W, on<0,4Ω(5A), 60/150ns	17p	TO-220	2SK925...26, 2SK1393, 2SK1761
2 SK 1222	Fjd	MOS-N-FET-e	VFET, 450/30V, 15A, 125W, on<0,55Ω(6A), 140/240ns	18p	TO-3P	2SK899, 2SK1610, 2SK1678, 2SK1757,++
2 SK 1223	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 50/100A, 130W, <45mΩ(13A)	77p	TOP-3L	2SK1380
2 SK 1224	Fjd	MOS-N-FET-e	VFET, 800/30V, 4A, 50W, on<4,5Ω(2A), 95/190ns	17c(p)	TO-3P	2SK1501, 2SK1639, 2SK1643, 2SK1807
2 SK 1225	Hit	MOS-N-FET-e*	=2SK556: Iso, 60W	=18c	(TO-3PFM)	2SK1268...69, 2SK1328, 2SK1523...24
2 SK 1227	Tos	N-FET	C-Mic Imp, 15V, Zin>200MΩ, Ur<40mV	41a	-	-
2 SK 1228	Mat	MOS-N-FET-e	SMD, S, 50/10V, 50/100mA, <50Ω(10mA), 200/200ns	35a	SOT-23	BSS 138, BSS 145, BST 82, 2SK2158
2 SK 1229	Hit	GaAs-N-FET	SHF, 4V, 60mA, Idss=12...60mA, Up=0,3...2,5V F<1,3/Gp>9dB(12GHz)	51(SGSD)	SOT-173	-
2 SK 1230	Hit	MOS-N-FET-e*	=2SK551: Iso, 25W	17c	SOT-186	2SK525, 2SK1035
2 SK 1231	Hit	MOS-N-FET-e*	=2SK552: Iso, 30W	17c	SOT-186	2SK1351, 2SK1608, 2SK1626...27
2 SK 1232	Hit	MOS-N-FET-e*	=2SK553: Iso, 30W	17c	SOT-186	2SK1351, 2SK1608, 2SK1627
2 SK 1233	Say	GaAs-N-FET	UHF, 6V, 0,1A, Idss=20...90mA, Up=0,5...5V F=2dB(8GHz), Gp=11dB(4GHz)	51(SGSD)	-SOT-173	-
2 SK 1234	Say	GaAs-N-FET	UHF, 5V, 0,1A, Idss=20...80mA, Up=0,5...5V F=1,6dB(8GHz), Gp=13dB(4GHz)	51(SGSD)	-SOT-173	-
2 SK 1235	Say	GaAs-N-FET	UHF, 6V, 0,1A, Idss=20...90mA, Up=0,5...5V F<3/Gp>5dB(12GHz)	51(SGSD)	-SOT-173	-
2 SK 1236	Say	GaAs-N-FET	UHF, 6V, 0,1A, Idss=20...90mA, Up=0,5...5V F<2,8/Gp>6,3dB(12GHz)	51(SGSD)	-SOT-173	-
2 SK 1237	Say	GaAs-N-FET	UHF, 5V, 0,1A, Idss=20...80mA, Up=0,5...3V F=1,8/Gp=7dB(12GHz)	51(SGSD)	-SOT-173	-
2 SK 1238	Say	GaAs-N-FET	UHF, 5V, 0,07A, Idss=20...60mA, Up=0,5...2,5V F=1,5/Gp=8dB(12GHz)	51(SGSD)	-SOT-173	-
2 SK 1239	Say	GaAs-N-FET	=2SK1238:	52(SGSD)	SOT-100	-
2 SK 1240	Say	GaAs-N-FET	UHF, X-Band, 0,06A, Idss=10...60mA, Up=0,5...2,5 F<1,4/Gp>9dB(12GHz)	51(SGSD)	-SOT-173	-
2 SK 1241	Say	GaAs-N-FET	UHF, X-Band, 0,06A, Idss=10...60mA, Up=0,5...2,5 F<1,4/Gp>9dB(12GHz)	51(SGSD)	-SOT-173	-
2 SK 1242	Say	GaAs-N-FET	=2SK1240:	52(SGSD)	SOT-100	-
2 SK 1243	Say	GaAs-N-FET	=2SK1241:	52(SGSD)	SOT-100	-
2 SK 1244	Shi	MOS-N-FET-e	VFET, 500/30V, 3A, 40W, on<2,3Ω, 45/75ns	17p	TO-220	2SK1154, 2SK1494
2 SK 1245	Shi	MOS-N-FET-e	=2SK1244: Iso	15c	(ITO-220)	BUK 445-500, 2SK1572, 2SK1767
2 SK 1246	Shi	MOS-N-FET-e	VFET, 500/30V, 5A, 50W, on<1,4Ω, 50/90ns	17p	TO-220	BUZ 41A, BUZ 90, 2SK1156, 2SK1751,++
2 SK 1247	Shi	MOS-N-FET-e	=2SK1246: Iso	15c	(ITO-220)	2SK1232, 2SK1351, 2SK1608, 2SK1627,++
2 SK 1248	Shi	MOS-N-FET-e	VFET, 500/30V, 10A, 100W, on<0,7Ω, 70/143ns	16p	(MTO-3P)	2SK724, 2SK896, 2SK1488, 2SK1753,++
2 SK 1249	Shi	MOS-N-FET-e	VFET, 500/30V, 15A, 130W, on<0,45Ω, 100/200ns	16p	(MTO-3P)	BUZ338, 2SK725, 2SK899, 2SK1610, 2SK1745
2 SK 1250	Shi	MOS-N-FET-e	VFET, 500/30V, 20A, 150W, on<0,35Ω, 130/260ns	16p	(MTO-3P)	2SK1169...70, 2SK1497...1500, 2SK1680, ++
2 SK 1251	Tos	MOS-N-FET-e*	VFET, 60/20V, 5/20A, 10W, <0,24Ω(2,5A), 13/200ns	=14c	SOT-82	-
2 SK 1252	Tos	MOS-N-FET-e*	VFET, 120/20V, 3/12A, 10W, <0,58Ω(1,5A), 11/120ns	=14c	SOT-82	-
2 SK 1253	Hit	MOS-N-FET-e*	VFET, LogL, 30/20V, 30A, 35W, <0,03Ω(15A), 155/700ns	17c	SOT-186	2SK1262
2 SK 1254(L,S)	Hit	MOS-N-FET-e*	VFET, LogL, 100/20V, 3/12A, 20W, <0,4Ω(2A), 25/195ns	30p	TO-251,252	2SK1113, 2SK1284
2 SK 1255	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 5/10A, 30W, <0,3Ω(2A), 29/150ns	17c	SOT-186	BUK 541-60, BUK 542-100, 2SK1260
2 SK 1256	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 10A, 40W, <0,165Ω(3A), 46/330ns	17c	SOT-186	2SK1033, 2SK1093, 2SK1305, 2SK1344,++
2 SK 1257	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 40/80A, 45W, on<0,05Ω(10A)	17c	SOT-186	2SK1653, 2SK1952
2 SK 1258	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 50/100A, 100W, on<45mΩ(13A)	18p	TO-3P	2SK1379, 2SK1381
2 SK 1259	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 100/200A, 150W, on<23mΩ(25A)	77p	TOP-3L	-
2 SK 1260	Mat	MOS-N-FET-e	VFET, LogL, 100/20V, 5/10A, 30W, <0,6Ω(2A), 26/120ns	17c	SOT-186	BUK 542-100, 2SK1265
2 SK 1261	Mat	MOS-N-FET-e	VFET, LogL, 100/20V, 8/16A, 40W, <0,3Ω(3A), 33/280ns	17c	SOT-186	BUK 543-100, 2SK1556
2 SK 1262	Mat	MOS-N-FET-e	VFET, LogL, 100/20V, 30/60A, 45W, on<85mΩ(10A)	17c	SOT-186	-
2 SK 1263	Mat	MOS-N-FET-e	VFET, LogL, 100/20V, 40/80A, 100W, on<75mΩ(13A)	18p	TO-3P	2SK1304, 2SK1381
2 SK 1264	Mat	MOS-N-FET-e	VFET, LogL, 150/20V, 3/6A, 30W, <1,3Ω(2A), 24/132ns	17c	SOT-186	-
2 SK 1265	Mat	MOS-N-FET-e	VFET, LogL, 150/20V, 6/12A, 40W, <0,6Ω(3A), 29/300ns	17c	SOT-186	BUK 545-200, 2SK1035
2 SK 1266	Mat	MOS-N-FET-e	VFET, LogL, 150/20V, 20/40A, 45W, on<135mΩ(10A)	17c	SOT-186	2SK2098
2 SK 1267	Mat	MOS-N-FET-e	VFET, LogL, 150/20V, 25/50A, 100W, on<0,13Ω(12A)	18p	TO-3P	-
2 SK 1268	Hit	MOS-N-FET-e*	=2SK559: Iso, 60W	=18c	(TO-3PFM)	2SK1331, 2SK1453, 2SK1524
2 SK 1269	Hit	MOS-N-FET-e*	=2SK560: Iso, 60W	=18c	(TO-3PFM)	2SK1331, 2SK1524
2 SK 1270	Hit	MOS-N-FET-e	=2SK975: 2A, 10W	14b	TO-126	2SK1283
2 SK 1271	Nec	MOS-N-FET-e	VFET, 1400/20V, ±5A, 240W, <4Ω(3A), 55/260ns	18p	TO-3P	-
2 SK 1272	Nec	MOS-N-FET-e*	VFET, LogL, 60/20V, ±1/2A, 0,75W, on<0,65Ω(0,5A)	7b	TO-92	2SK1274, 2SK1733
2 SK 1273	Nec	MOS-N-FET-e*	=2SK1272: SMD, ±2/4A	39b	SOT-89	2SK1311, 2SK1470, 2SK1717, 2SK2315
2 SK 1274	Nec	MOS-N-FET-e*	=2SK1272: ±1,5/3A, 1W	9c	(SP-8)	2SK975, 2SK1733, 2SK1736
2 SK 1275	Hit	MOS-N-FET-e*	=2SK1199: Iso, 30W	17c	SOT-186	2SK1143, 2SK1459
2 SK 1276	Fjd	MOS-N-FET-e	VFET, 250/20V, 20A, 100W, on<0,2Ω(10A), 80/300ns	18p	TO-3P	2SK901, 2SK944, 2SK1641, 2SK1673...74
2 SK 1277	Fjd	MOS-N-FET-e	VFET, 250/20V, 30A, 150W, on<0,12Ω(15A), 175/600ns	18p	TO-3P	2SK902, 2SK1492, 2SK1671, 2SK1675...76
2 SK 1278	Fjd	MOS-N-FET-e	VFET, 500/20V, 10A, 100W, on<1,1Ω(5A), 85/290ns	18p	TO-3P	BUZ339, 2SK724, 2SK896, 2SK1488, 2SK1753
2 SK 1279	Fjd	MOS-N-FET-e	VFET, 500/20V, 15A, 125W, on<0,58Ω(8A), 130/560ns	18p	TO-3P	BUZ 338, 2SK1610, 2SK1678, 2SK1757,++
2 SK 1280	Fjd	MOS-N-FET-e	VFET, 500/20V, 18A, 150W, on<0,5Ω(9A), 185/630ns	18p	TO-3P	2SK1409, 2SK1411, 2SK1680, 2SK2057,++