

BA 379	Phi,Sie,Tho	PIN-Di	VHF/UHF, 30V, 20mA, Uf<1V(20mA), 0,3pF(0V/900MHz)	(31a)	SOD-52				BA 382, MPN 3401, MPN 3402
BA 382	Mot	PIN-Di	VHF/UHF, VHF Band-S, 40V, 0,75pF(1V), 0,34Ω(10mA)	71a(4mm)	=SOD-23				MPN 3401, MPN 3402
BA 389	Sie	PIN-Di	1MHz...1GHz, 30V, 50mA, 0,55pF(10V), 5Ω(10V/100MHz)	31a	DO-35				BA 479
BA 401	Rhm	LIN-IC	TV, Sound IF, FM IF, Ucc=12V	5-SIP		BA 401 *		5-SIP	-
BA 401 F	Rhm	LIN-IC	=BA 401: SMD	8-MDIP					-
BA 402	Rhm	LIN-IC	TV, Sound IF, FM IF	7-SIP		BA 402 *		7-SIP	-
BA 403	Rhm	LIN-IC	FM IF, Demodulator, Ucc=8...15V	7-SIP		TA 7130 P		7-SIP	KA 2245, LA 1150, TA 7130P, µPC 1028H
BA 404	Rhm	LIN-IC	FM IF	9-SIP					KA 2244, TA 7303
BA 423	Phi	C-Di	AM-Band-S, 20V, 50mA, <2,5pF(3V), <1,2Ω(10mA)	31a	DO-34				BA 223
BA 423 L		C-Di	=BA 423	72a(3,4mm)	SOD-80				-
BA 479(A,G,S)	Aeg	PIN-Di	10...1000MHz, 30V, 50mA, <0,5pF(0V), <50Ω(1,5mA)	71a(4mm)	SOD-23				BA 389
BA 480	Phi	Si-Di	Schottky, UHF Mx, 4/5V, 30mA, Uf<0,28V(1mA)	31a	DO-34				BAR 19, BAT 29, BAT 45, 1S1925
BA 481	Phi	Si-Di	Schottky, UHF Mx, 4/5V, 30mA, <0,45V(1mA)	31a	DO-34				BAR 19, BAT 29, BAT 45, 1S1925
BA 482	Phi,Tho	C-Di	VHF Band-S, 35V, 0,1A, <1,2pF(3V), <0,7Ω(3mA)	31a	DO-34				BA 243, BA 283, BA 483...484, 1SS152,++
BA 483	Phi,Tho	C-Di	VHF Band-S, 35V, 0,1A, <1pF(3V), <1,2Ω(3mA)	31a	DO-34				BA 243, BA 283, BA 483...484, 1SS152,++
BA 484	Phi,Tho	C-Di	VHF Band-S, 35V, 0,1A, <1,6pF(3V), <1,2Ω(3mA)	31a	DO-34				BA 243, BA 283, BA 483...484, 1SS152,++
BA 501	Rhm	LIN-IC	Audio Out, 18V, 1,5A, 4W(13V/4Ω)	8-SIL					-
BA 505	Rhm	LIN-IC	Audio Drv	14-DIP+g					-
BA 505 G	Sie	Si-Di	CATV, VHF Tuning						-
BA 511(A)	Rhm	LIN-IC	Audio Out, 4,5W(13V/4Ω)	10-SIL		BA 532		10-SIL	BA 532
BA 514	Rhm	LIN-IC	Audio Inp+Out, 2W(9V/4Ω)	8-SIL		BA 514 *		8-SIL	-
BA 515	Rhm	LIN-IC	Audio Out, 15V, 0,23W(3V/4Ω)	12-SQP					-
BA 516	Rhm	LIN-IC	Audio Out, 0,35W(9V/8Ω)	9-SIP					BA 526, BA 527
BA 518	Rhm	LIN-IC	Audio Out, 1,5W(12V/8Ω)	8-SIL					BA 547
BA 521(S)	Rhm	LIN-IC	Audio Out, 5,8W(13V/4Ω), S=verbessert/improved	10-SIL		BA 532		10-SIL	BA 532
BA 524	Rhm	LIN-IC	Audio Out, 3,8W(12V/4Ω)	10-SIL					-
BA 526	Rhm	LIN-IC	Audio Out, 0,43W(6V/8Ω)	9-SIP					BA 527
BA 527	Rhm	LIN-IC	Audio Out, 0,8W(6V/4Ω)	9-SIP					KIA 6278S
BA 532	Rhm	LIN-IC	Audio Out, 5,8W(13V/4Ω)	10-SIL		BA 532		10-SIL	-
BA 534	Rhm	LIN-IC	Audio Out, 2,3W(9V/4Ω)	10-SIL					BA 524
BA 535	Rhm	LIN-IC	2x Audio Out, 20V, 2x4,8W(12V/4Ω)	12-SILP					(BA 536)
BA 536	Rhm	LIN-IC	2x Audio Out, 2x4,5W(12V/4Ω)	12-SILP					BA 5402(A)
BA 546	Rhm	LIN-IC	Audio Out, 12V, 0,33W(6V/8Ω)	9-SIP					BA 527
BA 547	Rhm	LIN-IC	Audio Out, 1,5W(12V/8Ω)	8-SIL					BA 518
BA 555	Rhm	LIN-IC	=NE 555	8-DIP		NE 555 N		8-DIP	=NE 555
BA 567	Rhm	LIN-IC	=LM 567CN	8-DIP		LM 567			=LM 567CN
BA 579 A	Tho	PIN-Di	SMD, Dual, VHF/UHF, 30V, 20mA, 0,35pF(1V), 4,5Ω	35n	SOT-23				-
BA 579 C(K)		PIN-Di	=BA 579A:	35f	SOT-23				-
BA 579 S		PIN-Di	=BA 579A:	35t	SOT-23				-
BA 582	Phi,Sie	C-Di	SMD, TV, VC, VHF Band-S, 35V, <1,4pF(1V), <0,7Ω	71a(2,7mm)	SOD-123				1SS241
BA 585	Sie	PIN-Di	HF Att, 50V, 50mA, 1...2000MHz, <0,4pF(0V)	71a(2,7mm)	SOD-123				-
BA 586	Sie	PIN-Di	HF Att, 50V, 50mA, >1MHz, <0,35pF(0V)	71a(2,7mm)	SOD-123				-
BA 592	Sie	C-Di	=BA 582:	71a(1,7mm)	SOD-323				1SS314, 1SS356
BA 595	Sie	PIN-Di	=BA 585:	71a(1,7mm)	SOD-323				-
BA 596	Sie	PIN-Di	=BA 586:	71a(1,7mm)	SOD-323				-
BA 604	Aeg	Si-Di	SMD, Uni, S, 50V, 0,2/0,45, Uf<1,1V(50mA), <20ns	72a(3,4mm)	SOD-80				-
BA 612	Rhm	LIN-IC	5x PNP Darl.-Transistor, 26V, 0,4A, hFE>2000	14-DIP					-
BA 614(A)	Rhm	LIN-IC	6x PNP Darl.-Trans., 20V, 0,1A, Usat<2,2V(75mA)	14-DIP					-
BA 618	Rhm	LIN-IC	7x LED/LCD Drv, Ucc=10V, 0,1A	16-DIP					-
BA 621	Rhm	LIN-IC	Analog-Schalter/Switch	5-SIP					-
BA 631	Rhm	LIN-IC	FM Intercom	14-DIP					-
BA 634	Rhm	LIN-IC	T-Flipflop, Reset, Ucc=-16V	5-SIP					-
BA 634 F		LIN-IC	=BA 634: SMD	8-MDIP					-
BA 653	Rhm	LIN-IC	Berührungsschalter/Touch Sensor	16-DIP					-
BA 656	Rhm	LIN-IC	LED Linear-Meter, 5 LED	9-SIP					(KA 2286, LB 1413)
BA 658	Rhm	LIN-IC	12P, VU-Meter Drv(FLT Display)	16-DIP					-
BA 664	Rhm	LIN-IC	6x Uni Drv, Ucc=20V, 0,1A, Usat<2,2V(75mA)	14-DIP					-
BA 668(A)	Rhm	LIN-IC	12P, VU-Meter Drv(FLT Display), Peak Hold, Ucc=16V	18-DIP					-
BA 679(S)	Aeg	PIN-Di	=BA 479(A,G,S): SMD	72a(3,4mm)	SOD-80				BA 979
BA 681 A	Rhm	LIN-IC	LED Linear-Meter Drv, 12 LED, Ucc=12V	18-DIP					-
BA 682	Itt,Sie,++	C-Di	=BA 282: SMD	72a(3,4mm)	SOD-80				BA 982
BA 682 A	Rhm	LIN-IC	LED VU-Meter Drv, 12 LED, Ucc=12V	18-DIP					-
BA 682 AF	Rhm	LIN-IC	=BA 682A: SMD	18-MDIP					-
BA 683	Itt,Sie,++	C-Di	=BA 283: SMD	72a(3,4mm)	SOD-80				BA 983
BA 683 A	Rhm	LIN-IC	LED Level-Meter Drv, 12 LED, Ucc=12V	18-DIP					-
BA 684 A	Rhm	LIN-IC	LED Linear-Meter Drv, 8 LED, Ucc=12(6,5...14)V	16-DIP					-
BA 685	Rhm	LIN-IC	LED Linear Meter Drv, 5 LED, Ucc=13(6,5...14)V	16-DIP					-
BA 689	Rhm	LIN-IC	LED Linear-Meter Drv, 12 LED, Ucc=12V	18-DIP					-
BA 695	Rhm	LIN-IC	AM/FM LED/LCD Tuning Indicator, 3 LED, Ucc=12V	9-SIP					-
BA 704	Rhm	Z-IC	2,65V, 1,5mA, ±0,3mV/°C	7b	TO-92				-
BA 707	Rhm	Z-IC	3,3V, 1,8mA, ±0,3mV/°C	7b	TO-92				-
BA 714	Rhm	Z-IC	3,3V, 50...250µA	9d	(FTR)				-
BA 715	Rhm	OP-IC	Dual, Serie 158	9-SIP					-
BA 718	Rhm	OP-IC	Dual	9-SIP					-
BA 728	Rhm	OP-IC	Dual, lo-power, ±9V, -20...+75°	8-DIP					-
BA 728 F		OP-IC	=BA 728: SMD	8-MDIP					-
BA 728 N		OP-IC	=BA 728: Fig. >	8-SIP					-
BA 735 F	Rhm	OP-IC	Dual	8-MDIP					-
BA 779(S)	Aeg	PIN-Di	=BA 479G(S): SMD	35p	SOT-23				-
BA 779-2		PIN-Di	=BA 479(S): SMD, Dual	35t	SOT-23				-
BA 802	Rhm	LIN-IC	PLL Motor Controller	5-SIP					-
BA 806	Rhm	LIN-IC	PLL Motor Controller	5-SIP					-
BA 820	Rhm	LIN-IC	8-Bit Serial In Parallel Out Driver	16-DIP					-
BA 823	Rhm	LIN-IC	8-Bit Serial In Parallel Out Driver, Ucc=5V	16-DIP					-
BA 823 F		LIN-IC	=BA 823: SMD	16-MDIP					-
BA 829	Rhm	LIN-IC	8-Bit Serial In Parallel Out Driver, Ucc=5V	18-DIP					-
BA 841	Rhm	LIN-IC	VC, Servo						-
BA 842	Rhm	LIN-IC	Recordersteuerung/Tape Deck Controller	40-DIP					-
BA 843	Rhm	LIN-IC	Recorder, Tastenstrg./Key Controller,Ucc=4,5...5,5V	16-DIP					-
BA 843 F		LIN-IC	=BA 843: SMD	16-MDIP					-
BA 845	Rhm	LIN-IC	Recorderspeicher/Memory	24-DIP					-
BA 847	Rhm	LIN-IC	VC-Servo, Bildschnitt/Special Playback	22-DIP					-
BA 852	Rhm	LIN-IC	VC, Servo Ctrl., FG System	16-DIP					-