

HA 178 M05(P,PJ)...	Hit	Z-IC	+5V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7805/TO-220	17b	...	78M05... (TO-220)
HA 178 M06(P,PJ)...	Hit	Z-IC	+6V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7806/TO-220	17b	...	78M06... (TO-220)
HA 178 M07(P,PJ)...	Hit	Z-IC	+7V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220			...	78M07... (TO-220)
HA 178 M08(P,PJ)...	Hit	Z-IC	+8V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7808/TO-220	17b	...	78M08... (TO-220)
HA 178 M09(P,PJ)...	Hit	Z-IC	+9V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7809/TO-220	17b	...	78M09... (TO-220)
HA 178 M12(P,PJ)...	Hit	Z-IC	+12V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7812/TO-220	17b	...	78M12... (TO-220)
HA 178 M15(P,PJ)...	Hit	Z-IC	+15V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7815/TO-220	17b	...	78M15... (TO-220)
HA 178 M18(P,PJ)...	Hit	Z-IC	+18V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7818/TO-220	17b	...	78M18... (TO-220)
HA 178 M20(P,PJ)...	Hit	Z-IC	+20V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7820/TO-220	17b	...	78M20... (TO-220)
HA 178 M24(P,PJ)...	Hit	Z-IC	+24V, 0,5A, ±4%, A=±2%, B=±3%, C=+2/-4%	17b	TO-220	7824/TO-220	17b	...	78M24... (TO-220)
HA 178 MxxFM,FMP	Hit	Z-IC	=HA 178 M05...M24(P,PJ): Iso	17b	TO-220 Iso			...	78Mxx... (TO-220 Iso)
HA 179L05(P),A(PA)	Hit	Z-IC	-5V, 0,15A, ±4%, A=±2%	7a	TO-92L	79L05/TO-92	7a	...	79L05(TO-92)
HA 179L06(P),A(PA)	Hit	Z-IC	-6V, 0,15A, ±4%, A=±2%	7a	TO-92L			...	79L06(TO-92)
HA 179L08(P),A(PA)	Hit	Z-IC	-8V, 0,15A, ±4%, A=±2%	7a	TO-92L			...	79L08(TO-92)
HA 179L09(P),A(PA)	Hit	Z-IC	-9V, 0,15A, ±4%, A=±2%	7a	TO-92L			...	79L09(TO-92)
HA 179L10(P),A(PA)	Hit	Z-IC	-10V, 0,15A, ±4%, A=±2%	7a	TO-92L			...	79L10(TO-92)
HA 179L12(P),A(PA)	Hit	Z-IC	-12V, 0,15A, ±4%, A=±2%	7a	TO-92L	79L12/TO-92	7a	...	79L12(TO-92)
HA 179L15(P),A(PA)	Hit	Z-IC	-15V, 0,15A, ±4%, A=±2%	7a	TO-92L			...	79L15(TO-92)
HA 179 L05...L15UA	Hit	Z-IC	=HA 179L05...L15: Min	39a	SOT-89			...	79Lxx (SOT-89)
HA 179 M05 FM,FMP	Hit	Z-IC	Iso, -5V, 0,5A	17c	TO-220 Iso	(7905/TO-220) ³	17c	...	79M05... (TO-220 Iso)
HA 179 M06 FM,FMP	Hit	Z-IC	Iso, -6V, 0,5A	17c	TO-220 Iso			...	79M06... (TO-220 Iso)
HA 179 M06 FM,FMP	Hit	Z-IC	Iso, -12V, 0,5A	17c	TO-220 Iso	(7912/TO-220) ³	17c	...	79M12... (TO-220 Iso)
HA 179 M15 FM,FMP	Hit	Z-IC	Iso, -15V, 0,5A	17c	TO-220 Iso	(7915/TO-220) ³	17c	...	79M15... (TO-220 Iso)
HA 1107	Hit	LIN-IC	VC, Sound IF						
HA 1108	Hit	LIN-IC	TV, AFT	14-DIP					
HA 1110	Hit	LIN-IC	Video-Verstärker/Amplifier	TO-101				CA 3001	
HA 1115	Hit	LIN-IC	Stereo-Decoder	14-DIP				HA 1120	
HA 1120	Hit	LIN-IC	Stereo-Decoder	14-DIP				HA 1115	
HA 1124	Hit	LIN-IC	TV, Sound IF	14-DIP				-HA 1125	
HA 1125	Hit	LIN-IC	TV, Sound IF	14-DIP				AM 241, CA 3065, KA 2101, LA 1365, LM 3065, MC 1358, TA 7176, ULN 2165	
HA 1126	Hit	LIN-IC	TV, AFT	14-DIP				LA 1364, M 5135, TA 7070	
HA 1127(P)	Hit	LIN-IC	TV, 5x Trans.-Array, 20/15V, 50mA, 460MHz	14-DIP,DIP				CA 3045	
HA 1127 FP	Hit	LIN-IC	=HA 1127(P): SMD	14-MDIP					
HA 1137(W)	Hit	LIN-IC	FM IF, LF Inp, AFC	16-DIP					
HA 1138	Hit	LIN-IC	AM Inp,Mx,Os,IF, Demodulator	16-DIP					
HA 1142	Hit	LIN-IC	Stereo-Decoder	14-DIP					
HA 1144	Hit	LIN-IC	TV, Video IF	14-DIP					
HA 1148	Hit	LIN-IC	CTV, VA Korrektur/Correction	14-DIP					
HA 1149	Hit	LIN-IC	FM Muting	14-DIP					
HA 1150	Hit	LIN-IC	FM IF	16-DIP					
HA 1151	Hit	LIN-IC	AM HF, IF	14-DIP					
HA 1152	Hit	LIN-IC	CTV, Video IF	14-DIP					
HA 1154	Hit	LIN-IC	VC, Sound IF						
HA 1156(W)	Hit	LIN-IC	Stereo-Decoder	14-DIP					
HA 1160	Hit	LIN-IC	TV, HA Sync, HA Os	7-SIP					
HA 1166(W)	Hit	LIN-IC							
HA 1167	Hit	LIN-IC							
HA 1173	Hit	LIN-IC	FM Demodulator	14-DIP					
HA 1190	Hit	LIN-IC	Sensor f. 4 Tasten/Touch Switches	16-DIP	SAS 560 S		16-DIP	SAS 560S	
HA 1194	Hit	LIN-IC	Sensor f. 4 Tasten/Touch Switches	16-DIP	SAS 570 S		16-DIP	SAS 570S	
HA 1196	Hit	LIN-IC	Stereo-Decoder	16-DIP					
HA 1197	Hit	LIN-IC	AM Tuner, IF	16-DIP		HA 1197*	16-DIP		
HA 1199	Hit	LIN-IC	AM Tuner	16-DIP		HA 1199*	16-DIP		
HA 1201	Hit	LIN-IC	FM IF	8-DIP				(=HA 1211) ¹⁰	
HA 1202	Hit	LIN-IC	FM IF	8-DIP					
HA 1203	Hit	LIN-IC	FM IF	8-DIP					
HA 1211	Hit	LIN-IC	FM IF	8-SIP		HA 1211*	8-SIP	(=HA 1201) ¹⁰	
HA 1303	Hit	OP-IC		TO-100					
HA 1306(W)	Hit	LIN-IC	Audio Out, 18V, 2,25A, 3,5W(13V/4Ω)	10-QIP+f					
HA 1314	Hit	LIN-IC							
HA 1317(V,W,VU,WU)	Hit	LIN-IC	Audio Out, 36V, 8W(26V/8Ω)	10-DIP+g					
HA 1319	Hit	LIN-IC	Audio Inp,Out, 12V, 1W(6V/4Ω)	14-DIP					
HA 1322(W)	Hit	LIN-IC	Audio Out, 18V, 2,25A, 5,5W(13V/4Ω)	10-DIP+f					
HA 1324	Hit	LIN-IC	Audio Out, 18V, 2,25A, 4,5W(13V/4Ω)	10-DIP+g					
HA 1325	Hit	LIN-IC	Audio Out, 20V, 1,25A, 2W(13V/8Ω)	12-DIP+a					
HA 1327	Hit	LIN-IC	4-Kanal-/Channel Decoder	16-DIP					
HA 1328	Hit	LIN-IC	Matrix f. 4-Kanal-/Channel Decoder	16-DIP					
HA 1329	Hit	LIN-IC	Audio Out, 9V, 1,4A, 2,5W(6V/8Ω)	12-DIP+a					
HA 1333	Hit	LIN-IC	CD-4 Demodulator	16-DIP					
HA 1334	Hit	LIN-IC	CD-4 Demodulator	16-DIP					
HA 1338	Hit	LIN-IC	Audio Out, 33V, 4,1A, 6W(24V/8Ω)	10-QIP+f					
HA 1339(A)	Hit	LIN-IC	Audio Out, 18V, 4,5A, 5,5W(13V)	10-SILP+a					
HA 1339(A)R	Hit	LIN-IC	=HA1339: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a					
HA 1342(A)	Hit	LIN-IC	Audio Out, 18V, 4,5A, 5,5W(13V)	10-SILP+a					
HA 1342(A)R	Hit	LIN-IC	=HA1342: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a					
HA 1345 V	Hit	LIN-IC	Audio Out, 36V, 8W(26V/8Ω)	10-SILP					
HA 1350	Hit	LIN-IC	Audio Out, ±30V, 7,5A, 18W(±25V/8Ω)	10-SILP				HA 1370	
HA 1361	Hit	LIN-IC	Audio Out, 9V, 2,25A, 1W(6V/4Ω)	12-DIP+b					
HA 1364	Hit	LIN-IC	TV, Sound IF, LF Out, 1,5W(24V/16Ω)	12-QIP+b					
HA 1366 W	Hit	LIN-IC	Audio Out, 18V, 4,5A, 5,5W(13V/4Ω)	10-SILP+a					
HA 1366 WR	Hit	LIN-IC	=HA1366W: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a					
HA 1367(A)	Hit	LIN-IC	Recorder, Audio Inp,Out, 9V, 2,25A, 2,2W(6V/4Ω)	20-DIP+b					
HA 1368	Hit	LIN-IC	Audio Out, 18V, 4,5A, 5,3W(13V/4Ω)	10-SILP+a					
HA 1368 R	Hit	LIN-IC	=HA1368: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a		HA 1368*	10-SILP+a		
HA 1370	Hit	LIN-IC	Audio Out, ±30V, 7,5A, 18W(±25V/4...8Ω)	10-SILP					
HA 1371	Hit	LIN-IC	Audio Out, 15V, 3A, 7,3W(9V/4Ω)	12-QIP+b					
HA 1372	Hit	LIN-IC	Audio Out, 18V, 4,5A, 5,5W(13V/4Ω)	10-DIP+f					
HA 1374	Hit	LIN-IC	Dual Audio Out, 22V, 2,8A, 2x3W(15V/8Ω)	10-SILP+a					
HA 1374 A	Hit	LIN-IC	=HA 1374: 25V, 3,2A, 2x4W(17V/8Ω)	10-SILP+a					
HA 1377(A)	Hit	LIN-IC	Dual Audio Out, 18V, 4,5A, 2x5,8W(13V/4Ω)	12-SIL		HA 1377	12-SIL		
HA 1384(A)	Hit	LIN-IC	Audio Out, 18V, 4A, 20W(13,2V/4Ω, BTL)	12-SIL					
HA 1385	Hit	LIN-IC	CTV, VA Out, Ucc=110V	17/5Pin	TO-220/5				