

## WiFi Smart Light Switch | Dual

### General information

Traditional light switches just got a lot smarter. This Smart Wall Switch for Dual Lights allows you to remotely and automatically take control of two lights from one, discrete wall switch.

#### Easy to set up

The switch can be used to control your lights by simply using the touch buttons on it. But, it also allows you to connect it directly to your Wi-Fi router and gain control of two lights from your smartphone and tablet or by speaking, when used alongside Amazon Alexa or Google Home.

Note: Neutral wire required to always power the switch with 230V

#### Schedule and pair

The intuitive app that provides the brains behind this Smart Wall Switch for Dual Lights allows you to connect directly to your Wi-Fi router with no need for a separate hub. Through it you can pair your chosen lights to other appliances to create the perfect ambient setting in your room with just one command. Or, you can set the lights to turn on automatically – ideal if you are going to be away for a few days.

#### Discrete

The sleek and easy-to-clean glass front blends into your interior, and yet this discrete unit is powerful enough to support electrical lights of up to 300 W.

#### About Nedis® SmartLife

Discover a wide and ever-expanding range of products – such as bulbs, switches, sockets, sensors, and cameras – that can all be controlled through an easy-to-use and intuitive app. With voice control features supported by Amazon Alexa and Google Home, and no need for anything more than your existing Wi-Fi network, this is the connected, smart home made simple.

Whether you're looking for a single smart bulb or socket, or you want to automate your entire house, discover how



### Sales information

Order code: **WIFIWS20WT**  
 Product description: WiFi Smart Light Switch | Dual  
 Packaging: Giftbox with eurolock  
 Brand name: Nedis



Quantity	LxWxH (mm)	Weight
1	105x125x50	150 gr.
50	280x275x550	9750 gr.



## WiFi Smart Light Switch | Dual

accessible smart technology is today.

### Features

- Take remote, wireless control of two lights in your room – from just one Smart Wall Switch
- Durable – offers a lifetime of over 100,000 switch cycles
- Discrete – blends into your room's interior
- Powerful – allows you to schedule lighting, pair with other appliances and devices, and control with your voice (with Amazon Alexa or Google Home)
- Versatile – can be operated locally as a traditional wall light switch or remotely and automatically

### Specifications

Operating temperature:	-20 - 50 °C
Maximum radio transmit power:	19 dBm
Antenna gain:	2 dBi
Frequency range:	2412 - 2462 MHz
Internal depth:	25 mm
Hole spacing, mounting plate:	60 mm
Width:	86 mm
Height:	86 mm
Dimensions (Calculated):	10 mm (L) x 86 mm (W) x 86 mm (H)
Mounting:	Wall Mounting
Programming functions:	Switch On
Programming functions:	Switch Off
Programming functions:	Switch On with Time Delay
Programming functions:	Switch Off with Time Delay
Programming functions:	Button
App available for:	Android™ & iOS
Compatible with:	Nedis® SmartLife
Input voltage:	100 - 240 VAC 50 Hz
Number of outputs:	2
Colour:	White
Material:	Glass
Maximum power output:	300 W



## WiFi Smart Light Switch | Dual

Maximum power output:	300 W
Wireless technology:	Wi-Fi
Length:	10 mm

### Package contents

Smart dual wall switch  
Quick start guide