

- ✓ Ergonomic & compact 300 watt random orbit sander
- ✓ Ideal for working in confined spaces and over head
- ✓ Variable speed for optimum control
- ✓ Pad brake control: pad brake for a gauge free workpiece
- ✓ Convenient hook & loop paper fastening
- ✓ Very efficient dust extraction over 8 holes in the base plate
- ✓ Dust extraction, with dust bag or absorption system
- ✓ Soft-grip on handle

No load speed (rpm)	7000 - 12.000
Oscillation diameter (mm)	2,4
Oscillation rate (opm)	14.000 - 24.000
Power input (W)	300
Sanding pad size (mm)	125
Sound power level (Lwa)(dB(A))	91
Sound power level uncertainty (dB(A))	3
Sound pressure level (Lpa)(dB(A))	80
Sound pressure level uncertainty (dB(A))	3
Supplied in	Gift box
Vibration level (m/s ²)	7,4
Vibration uncertainty (m/s ²)	1,5
Weight (kg)	1,7

